

Nano-Power, RIO, 2.3V, Push-Pull Output Comparator with Voltage Reference

FEATURES

- Low supply current: 3.5 μ A(TYP) at Vs=2.3V
- Supply Range: +2.3V to +5.5V
- Integrated Voltage Reference: 1.2V
- Low input offset voltage: Vos(max) = 3.5mV
- Rail-to-Rail Input
- Push-Pull Output
- Operating Temperature Range: -40°C to +85°C
- Micro SIZE PACKAGES: SOT23-6

DESCRIPTION

The RS8912 is a push-pull output comparator. It features an uncommitted on-chip voltage reference and have low quiescent current, input common-mode range 200mV beyond the supply rails, and single-supply operation from 2.3V to 5.5V. The integrated 1.2V series voltage reference offers low 42 μ V/ $^{\circ}$ C drift, is stable with up to 10nF capacitive load, and can provide up to 350 μ A (TYP) of output current.

Featuring a push-pull output stage, the RS8912 allows for operation with absolute minimum power consumption when driving any capacitive or resistive load.

APPLICATIONS

- RC TIMERS
- MULTIVIBRATORS
- WINDOW DETECTORS
- SYSTEM MONITORING
- SENSOR SYSTEMS: Smoke Detectors, Light Sensors, Alarms


The RS8912 is available in Green SOT23-6 package and is specified at the full temperature range of -40°C to +85°C.

Device Information ⁽¹⁾

PART NUMBER	PACKAGE	BODY SIZE (NOM)
RS8912	SOT23-6	1.60mm × 2.92mm

(1) For all available packages, see the orderable addendum at the end of the data sheet.

Pin Configuration and Functions (Top View)



Pin Description

NAME	PIN	I/O ⁽¹⁾	DESCRIPTION
	SOT23-6		
OUT	1	O	Output
V-	2	P	Negative (lowest) power supply
+IN	3	I	Noninverting input
-IN	4	I	Inverting input
REF	5	O	Voltage Reference
V+	6	P	Positive (highest) power supply

(1) I=Input, O=Output, P=Power

SPECIFICATIONS

Absolute Maximum Ratings

Over operating free-air temperature range (unless otherwise noted) ⁽¹⁾

		MIN	MAX	UNIT
Voltage	Supply, Vs=(V+) - (V-)		7	V
	Input pin (IN+, IN-) ⁽²⁾	(V-)-0.5	(V+) +0.5	
	Signal output pin ⁽³⁾	(V-)-0.5	(V+) +0.5	
Current	Signal input pin (IN+, IN-) ⁽²⁾	-10	10	mA
	Signal output pin ⁽³⁾	-10	10	mA
	Output short-circuit ⁽⁴⁾	Continuous		
Temperature	Operating range, T _A	-40	85	°C
	Junction, T _J		150	
	Storage, T _{stg}	-65	150	

(1) Stresses above these ratings may cause permanent damage. Exposure to absolute maximum conditions for extended periods may degrade device reliability. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those specified is not implied.

(2) Input terminals are diode-clamped to the power-supply rails. Input signals that can swing more than 0.5V beyond the supply rails should be current-limited to 10mA or less.

(3) Output terminals are diode-clamped to the power-supply rails. Output signals that can swing more than 0.5V beyond the supply rails should be current-limited to ±10mA or less.

(4) Short-circuit to ground, one amplifier per package.

ESD Ratings

		VALUE	UNIT
V _(ESD)	Electrostatic discharge	Human-body model (HBM)	3000
		Machine Model (MM)	

Recommended Operating Conditions

Over operating free-air temperature range (unless otherwise noted)

	MIN	NOM	MAX	UNIT
Supply voltage, Vs= (V+) - (V-)	Single-supply	2.3	5.5	V
	Dual-supply	±1.15	±2.75	

Thermal Information:RS8912

THERMAL METRIC ⁽¹⁾		RS8912	UNIT
		6PINS	
		SOT23-6	
R _{θJA}	Junction-to-ambient thermal resistance	214.7	°C/W
R _{θJC(top)}	Junction-to-case(top) thermal resistance	127.1	°C/W
R _{θJB}	Junction-to-board thermal resistance	60.0	°C/W
Ψ _{JT}	Junction-to-top characterization parameter	33.4	°C/W
Ψ _{JB}	Junction-to-board characterization parameter	59.8	°C/W
R _{θJC(bot)}	Junction-to-case(bottom) thermal resistance	N/A	°C/W

PACKAGE/ORDERING INFORMATION

Orderable Device	Package Type	Pin	Channel	Op Temp(°C)	Device Marking	Package Qty
RS8912XH	SOT23-6	6	1	-40°C~85°C	8912 XXXX	Tape and Reel,3000

NOTE: XXXX = Date Code and Vendor Code.

ELECTRICAL CHARACTERISTICS: Vs=2.3V

(At $T_A = +25^\circ\text{C}$, $V_+ = 2.3\text{V}$, $V_- = 0\text{V}$, $V_{CM} = Vs/2$, unless otherwise noted.)

PARAMETER		CONDITIONS	RS8912			UNITS
			MIN	TYP	MAX	
POWER SUPPLY						
Vs	Operating Voltage Range		2.3		5.5	V
Iq	Quiescent Current			3.5	8	μA
PSRR	Power-Supply Rejection Ratio	Vs=2.3V to 5.5V, $V_{CM}=(V)+0.5\text{V}$		70		dB
INPUT						
Vos	Input Offset Voltage	V _{CM} = 0V		1	5	mV
		V _{CM} = 2.3V		1	5	
$\Delta Vos/\Delta T$	Input Offset Voltage Drift	V _{CM} = Vs/2, -40°C ≤ T _A ≤ 85°C		2		$\mu\text{V}/^\circ\text{C}$
IB	Input Bias Current			1	10	pA
V _{CM}	Common-Mode Voltage Range	T _A = -40°C to 85°C	(V-) - 0.1		(V+) + 0.1	V
CMRR	Power-Supply Rejection Ratio	V _{CM} = 0V to 2.3V		70		dB
OUTPUT						
V _{OH}	Output Swing From Upper Rail	I _O = 25 μA	2.208	2.237		V
		I _O = 95 μA	2.011	2.095		
V _{OL}	Output Swing From Lower Rail	I _O = 25 μA		55	80	mV
		I _O = 95 μA		205	289	
I _{SC}	Short Circuit Sink Current	Vs = 2.3V		-1	-0.62	mA
	Short Circuit Source Current	Vs = 2.3V	0.57	1		mA
SWITCHING						
T _{PHL}	Propagation Delay H To L	Overdrive = 10 mV		135		μs
		Overdrive = 100 mV		21		
T _{PLH}	Propagation Delay L To H	Overdrive = 10 mV		123		μs
		Overdrive = 100 mV		40		
T _R	Rise Time	Overdrive = 100 mV		30		us
T _F	Fall Time	Overdrive = 100 mV		30		us
	Noise of V _{REF}	f = 0.1Hz to 10Hz		20		μV_{RMS}
VOLTAGE REFERENCE						
V _{REF}	Reference Voltage	I _{REF} = 0mA	1.176	1.200	1.224	V
	Reference Voltage Drift			42		$\mu\text{V}/^\circ\text{C}$
	Reference Output Current (Source)		60	80		μA







ELECTRICAL CHARACTERISTICS: $V_S=5V$







(At $T_A = +25^\circ C$, $V+=5V$, $V-=0V$, $V_{CM}=Vs/2$, unless otherwise noted.)



PARAMETER	CONDITIONS	RS8912			UNITS
		MIN	TYP	MAX	
POWER SUPPLY					
V_S	Operating Voltage Range		2.3		5.5 V
I_Q	Quiescent Current			4.85	10 μA
PSRR	Power-Supply Rejection Ratio	$V_S=2.3V$ to $5.5V$, $V_{CM}=(V)+0.5V$		70	
INPUT					
V_{OS}	Input Offset Voltage	$V_{CM}=0V$		1	3.5
		$V_{CM}=5V$		1	3.5
$\Delta V_{OS}/\Delta T$	Input Offset Voltage Drift	$V_{CM}=Vs/2$, $-40^\circ C \leq T_A \leq 85^\circ C$		2	
I_B	Input Bias Current			1	10 pA
V_{CM}	Common-Mode Voltage Range	$T_A = -40^\circ C$ to $85^\circ C$	$(V)-0.1$		$(V)+0.1$ V
CMRR	Power-Supply Rejection Ratio	$V_{CM}=0V$ to $5V$		70	
OUTPUT					
V_{OH}	Output Swing From Upper Rail	$I_o=25\mu A$	4.915	4.935	
		$I_o=95\mu A$	4.720	4.785	
V_{OL}	Output Swing From Lower Rail	$I_o=25\mu A$		55	72
		$I_o=95\mu A$		215	280
I_{SC}	Short Circuit Sink Current	$V_S=5V$		-2.25	-2.2 mA
	Short Circuit Source Current	$V_S=5V$	2.15	2.23	
SWITCHING					
T_{PHL}	Propagation Delay H To L	Overdrive = 10 mV		67	
		Overdrive = 100 mV		12	
T_{PLH}	Propagation Delay L To H	Overdrive = 10 mV		68	
		Overdrive = 100 mV		12	
T_R	Rise Time	Overdrive = 100 mV		12	
T_F	Fall Time	Overdrive = 100 mV		12	
	Noise of V_{REF}	f=0.1Hz to 10Hz		20	μV_{RMS}
VOLTAGE REFERENCE					
V_{REF}	Reference Voltage	$I_{REF}=0mA$	1.176	1.200	1.224 V
	Reference Voltage Drift			42	
	Reference Output Current (Source)		200	350	

TYPICAL CHARACTERISTICS



At $T_A = +25^\circ\text{C}$, $V_s=5\text{V}$, $V_{CM} = V_s/2$, $C_L=15\text{pF}$ unless otherwise noted.









PACKAGE OUTLINE DIMENSIONS SOT23-6



RECOMMENDED LAND PATTERN (Unit: mm)



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	1.050	1.250	0.041	0.049
A1	0.000	0.100	0.000	0.004
A2	1.050	1.150	0.041	0.045
b	0.300	0.500	0.012	0.020
c	0.100	0.200	0.004	0.008
D	2.820	3.020	0.111	0.119
E	1.500	1.700	0.059	0.067
E1	2.650	2.950	0.104	0.116
e	0.950(BSC)		0.037(BSC)	
e1	1.800	2.000	0.071	0.079
L	0.300	0.600	0.012	0.024
θ	0°	8°	0°	8°